

Product information

RX101 BLUETOOTH MODULE



Now you can wirelessly send music stored on mobile phones (iPhone / iPod) or PCs supporting the Bluetooth standard A2DP, directly to your Marantz product – thanks to the new RX101 Bluetooth Module. It simply connects to the M-XPport and directs signals to your AV Receiver, Network Audio Player or System. And since the M-XPport also powers the module, no additional power adaptor is required. Check out the specifications section at the back of this catalogue to see which products have the M-XPport to connect the RX101.

Main Features

- Decodes Bluetooth A2DP audio signals from any Bluetooth device with A2DP protocol
- Decodes Bluetooth AVRCP signals to RC-5 for system control
- Output audio and RC-5 via dedicated Marantz M-XPport
- Build-in IR Receiver for hidden system control
- To be connected to M-XPport

EAN

EU/UK RX101/EX1B 4951035040621

because music matters

RX101 BLUETOOTH MODULE

RX101 is available on the following Marantz models that are equipped with the Marantz M-XPort:

- NR1402
- NR1602
- NR1601
- SR5004
- SR5005
- SR5006
- SR6004
- SR6005
- SR6006
- SR7005
- AV7005
- NA7004
- M-CR503
- M-CR603
- M-ER803

FEATURES	RX101
Communication method	Bluetooth ver2.1 + EDR
Transmission output	Bluetooth power class 2
Maximum transmission distance	10m
Transmission frequency band	2.4GHz to 2.4835 GHz
Supporting Bluetooth Profiles: A2DP/AVCHD	o/o
Supporting Codec	SBC
Supporting content protection	SCMS-T
Passcode	0000
Dual IR Receiver	o
DIN connector for M-XPort	o
GENERAL	
Color	Black
Weight	55g
Dimensions (W x H x D) in mm	60 x 30 x 60