

marantz®



NR1601 - Slim Design AV Receiver

Some people (or their partners) just don't want a big box in their living room. That's why Marantz created a slim-line AV Receiver. Which means now you can enjoy fabulous ear-cracking sound from an elegant slim-line box: the NR1601. But don't let appearances deceive you, this super-slim model packs as much punch as its big brothers, thanks to the discrete 7x 50W rms output and it creates a tidal wave of multichannel surround sound. On the video side, the four HDMI 1.4a inputs all support 3D video, while all analogue video signals are converted to HDMI level including I/P conversion. The set-up is easy - with the help of Audyssey MultEQ and Microphone - no need to study the manual, just follow the on-screen menu instructions. And, just like its bigger brothers, the NR1601 has an iPod-digital-compatible USB input, as well as an M-DAX2 to make the very most of sound quality from compressed audio. It all adds up to easy to use slim-line elegance with a powerful punch.

Main Features

- 7x 50 Watts RMS (8 ohm)
- Dolby TrueHD, DTS-HD Master Audio, ProLogic IIz
- HDMI v1.4a (3D) - 4in / 1out
- Audyssey MultEQ, Dynamic EQ and Dynamic Volume
- I/P scaling and videoconversion from analogue to HDMI
- iPod/iPhone compatible USB input iPod/iPhone compatible
- M-XPport for optional RX101 Bluetooth module

because music matters



| SPECIFICATIONS | NR1601 | | |
|---|--------------------------|--|---------------------|
| MULTICHANNEL SURROUND | | Variable cross over | 10 |
| THX Ultra II / Select II | -/- | Lip sync control | o |
| THX Surround EX | - | Multiroom zones | - |
| DTS HD / DTS 5.1 / DTS ES / DTS 96/24 | o/o/o/o | Front flap | - |
| Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / Dolby Pro-LogicIIz | o/o/o/o | Discrete RC coding (Main-/Multiroom) | o/- |
| Audyssey DSX | - | INPUTS/OUTPUTS | |
| Dolby Virtual Speaker / Neural Surround | o/o | VIDEO | |
| Multichannel Stereo | o | Composite In/Out | 3/1 |
| HT-EQ / Re-EQ | o/- | Component In/Out | 3/1 |
| DSD from SACD via HDMI | - | HDMI In/Out (version x.x) | 4/1 (1.4a) |
| Dolby Headphone | o | Multiroom Video Out: Composite/Component | -/- |
| Compressed audio enhancer: MDAX / MDAX2 | -/o | AUDIO | |
| SURROUND ENHANCEMENTS | | Analogue In/Out | 6/0 |
| Current Feedback Topology | - | Balanced In/Out | -/- |
| Hyper Dynamic Amplifier Modules (HDAM) | - | Phono MM In | - |
| Pure Direct | o | Digital Optical In/Out | 2/0 |
| Power Transformer: Toroidal/El | -/o | Digital Coaxial In/Out | 1/0 |
| High Grade Audio Components | - | Multiroom Out: analog/digital | -/- |
| Chassis: Copper plated / Metal | -/o | Multichannel Pre-Out/Main In | o(0.1ch)/- |
| NETWORK | | Subwoofer Out | 1 |
| DLNA certified | - | 7.1 Multichannel input | - |
| UPnP certified | - | OTHER | |
| Network Audio: MP3/WAV/AAC/FLAC/WMA | - | M-XPort for RX101 | o |
| Network static video (JPEG) | - | Speaker terminal: Gold plated screw/regular screw | -/o |
| Network video | - | Number of terminals | 9 |
| Internet radio: direct/external media player | - | Speaker A/B | o |
| vTuner/Napster/last.fm | - | Height speaker terminal | o |
| WiFi: integrated/external access point | - | Bi-amp drive (5.1 setting)/Speaker C | o/o |
| Ethernet | - | Marantz remote bus | o |
| IP Control | - | IR Receiver In / Emitter Out | -/- |
| Apple APP control by iPhone/iPod touch | - | IR Flasher In | o |
| OTHERS | | Network: IP-control/update | -/- |
| Bluetooth audio via RX101 | optional | RS-232c (control/update) | -/- |
| Auto speaker setup | Audyssey MultEQ | DC Triggers | - |
| Audyssey Dynamic EQ/Dynamic Volume | o/o | Front Inputs: Analogue audio / Composite / Digital Audio (opt.) / HDMI/USB | o(3.5mm jack)/-/-/o |
| Video Conversion | CVBS > HDMI; Comp > HDMI | USB Audio/Made for iPod/Works with iPhone | o/o/o |
| Interlace / progressive conversion | o (576i -> 576p) | SPECIFICATIONS | |
| Analogue to HDMI scaling | o(576p) | Power output (8/6 ohm RMS / 20Hz - 20kHz, 0,08%) | 50/60 Watts |
| HDMI to HDMI scaling | - | 70% Guarantee | - |
| Video processing | o | Audio Signal to Noise Ratio | 98dB |
| Picture adjust/noise reduction | -/- | FM Tuner | o |
| HDMI path-through on standby | o | GENERAL | |
| Deep Color pass through | o | Available colors: Gold/Silver/Black/Silver-Gold | -/-/o/o |
| 3D video pass through | o | Metal Front Panel | o |
| Audio Return Channel (ARC) | o | Backlit system remote control | RC010SR |
| CEC | o | Pre-programmed/Learnable/LCD Display | o/o/- |
| Front panel cursor control | o | Power Consumption in W | 250 |
| On Screen Display: GUI / OSD | -/o | Standby Consumption in W | 0.2 |
| | | Detachable power cable | o |
| | | Maximum Dimensions (W x D x H) in mm | 440 x 376 x 105 |
| | | Weight in kg | 9.0 |

because music matters